



# DT-3260

## SMART PEN TYPE DIGITAL MULTIMETER

### Safety Instructions

Input Limits	
Function	Maximum Input
VDC, VAC	600V DC or AC
mADC/AC	600mA DC or AC
Resistance, Capacitance, Diode test, Continuity	250V DC/AC

### General Specifications

The instrument complies with	EN61010-1
Insulation	Class2, Double insulation
Overvoltage category	CATIII 600V, CATII 1000V
Display	6000 counts LCD display with function indication
Polarity	Automatic. <-> negative polarity indmon
Over range	"01:" mark indication
Danger symbol	" " mark indication when the reading is exceeding 30V in ACV or DCV
Low battery indication	The "BAT" is displayed when the battery voltage drops below the operating level
Measurement rate	3 times per second (voltage mode)
Auto scan mode	The meter automatically selects the proper mode and range
Auto power off	Meter automatically shuts down after approx. 10 minutes of inactivity
Operating environment	0°C to 50°C (32°F to 122°F) at <70% relative humidity
Storage temperature	-20°C to 60°C (-4°F to 140°F)
For inside use, max height	at <80% relative humidity
Pollution degree	2000m
Power	2 (Two 1.5V button batteries, NEDA)
Dimensions	1604, IEC 6F22
Weight: Approx.	230(H) X 35(W) X 20(O) mm Approx.: 200g.

### Electrical Specifications

#### Electrical Characteristics for Scan Mode

Parameter	Test Condition	TypValue
AC/DC voltage scan mode sensitivity @1 KHz	10Mn Input impedance	400mV
RDC scan mode CAP sensitivity		400pF
RDC scan mode DIODE sensitivity	Forward voltage	o.sv

Accuracy is given at 18°C to 28°C (65°F to 83°F), less than 70% RH

#### DC Voltage (Auto-ranging)

Range	Resolution	Accuracy
600.0mV	0.1mV	±1.2% of rdg ± 5 dgts
6.000V	1mV	±1.5% of rdg ± 5 dgts
60.00V	10mV	
600.0V	100mV	

Input Impedance : 10Mn.  
Maximum Input : 600V de or 600V ac rms.

#### AC Voltage (Auto-ranging above 600mV)

Range	Resolution	Accuracy
600.0mV	0.1mV	±1.5% of rdg ± 30 dgts
6.000V	1mV	±1.5% of rdg ± 3 dgts
60.00V	10mV	±2.0% of rdg ± 3 dgts
600.0V	100mV	

Input Impedance : 10Mn.  
Frequency Range : 50 to 400Hz  
Maximum Input : 600V de or 600V ac rms.  
Note : The accuracy can not be assuring with the u600.0mvu range when the frequency range of AC Voltage is larger than 60Hz.

Contact :

#### CEM INSTRUMENTS (INDIA) PVT. LTD.

32A, Ganesh Chandra Avenue, 4th Floor, Kolkata-700013  
Tel: 033-22151376, 22159759  
Email: info@cem-instruments.in / info@cem-india.com  
Web: www.cem-instruments.in / www.cem-india.com

#### CEM INSTRUMENTS HEADQUATER & FACTORY

19th Building, 5th Region, Baiwangxin Industry Park,  
Songbai Road, Baimang, Xili, Nanshan, Shenzhen,  
China, 518108  
Tel: +86-755-27353188, Fax: +86-755-27653699



# DT-3260

## Smart Pen Type Digital Multimeter

### Electrical Specifications

#### DC Current (Auto-ranging for $\mu\text{A}$ and mA)

Range	Resolution	Accuracy
60.00mA	10 $\mu\text{A}$	$\pm 1.5\%$ of rdg $\pm 5$ dgts
600.0mA	100 $\mu\text{A}$	

Overload Protection : 0.8A/250V Fuse.

Maximum Input : 600mA dc or 600mA ac rms on mA ranges.

#### AC Current (Auto-ranging for $\mu\text{A}$ and mA)

Range	Resolution	Accuracy
60.00mA	10 $\mu\text{A}$	$\pm 2.0\%$ of rdg $\pm 5$ dgts
600.0mA	100 $\mu\text{A}$	

Overload Protection : 0.8A/250V Fuse.

Frequency Range : 40 to 400 Hz

Maximum Input : 600mA dc or 600mA ac rms on mA ranges.

#### Resistance (Auto-ranging)

Range	Resolution	Accuracy
600.0 $\Omega$	0.1 $\Omega$	$\pm 1.2\%$ of rdg $\pm 4$ dgts
6.000k $\Omega$	1 $\Omega$	$\pm 1.0\%$ of rdg $\pm 2$ dgts
60.00k $\Omega$	10 $\Omega$	$\pm 2.0\%$ of rdg $\pm 2$ dgts
600.0k $\Omega$	100 $\Omega$	
6.000M $\Omega$	1k $\Omega$	$\pm 2.5\%$ of rdg $\pm 3$ dgts
60.00M $\Omega$	10k $\Omega$	

Input Protection : 250V dc or 250V ac rms.

#### Capacitance (Auto-ranging)

Range	Resolution	Accuracy
6.000nF	1pF	$\pm 5.0\%$ of rdg $\pm 50$ dgts
60.00nF	10pF	$\pm 5.0\%$ of rdg $\pm 7$ dgts
600.0nF	0.1nF	$\pm 3.0\%$ of rdg $\pm 5$ dgts
6.000 $\mu\text{F}$	1nF	
60.00 $\mu\text{F}$	10nF	$\pm 5.0\%$ of rdg $\pm 5$ dgts
600.0 $\mu\text{F}$	0.1 $\mu\text{F}$	
6.000mF	1 $\mu\text{F}$	$\pm 5.0\%$ of rdg $\pm 5$ dgts
10.00mF	10 $\mu\text{F}$	$\pm 10.0\%$ of rdg $\pm 5$ dgts

The 6.000mF and 10.00mF range is not available for scan mode.

Input Protection : 250V dc or 250V ac rms.

### Accessories

Carrying Case, Testing Leads, Temperature Probe, Battery, Instruction Manual and Test Certificate.



#### Diode Test

Test current	Resolution	Accuracy
0.3mA typical	1 mV	$\pm 10\%$ of rdg $\pm 5$ dgts

Open circuit voltage : 2V DC typical. Beeper on :  $\leq 30\text{mV}$ .

Overload protection : 250V DC or AC rms.

#### Audible continuity

Audible Threshold: Less than 30 $\Omega$  Test current:  $< 0.3\text{mA}$

Overload protection: 250V dc or ac rms

#### Range

To switch the meter from AUTO-RANGING to MANUAL RANGING Modes and vice versa

#### Data Hold

To "freeze" a measurement for later reference.

#### MAX/MIN Record

It records the Maximum and Minimum Values

Contact :

**CEM INSTRUMENTS (INDIA) PVT. LTD.**

32A, Ganesh Chandra Avenue, 4th Floor, Kolkata-700013

Tel: 033-22151376, 22159759

Email: info@cem-instruments.in / info@cem-india.com

Web: www.cem-instruments.in / www.cem-india.com

**CEM INSTRUMENTS HEADQUARTER & FACTORY**

19th Building, 5th Region, Baiwangxin Industry Park,  
Songbai Road, Baimang, Xili, Nanshan, Shenzhen,  
China, 518108

Tel: +86-755-27353188, Fax: +86-755-27653699

