

DT-3348 True RMS 1000A AC/DC Watt Clamp Meter



Model 3348

3348 Professional True RMS 1000A AC/DC Watt Clamp Meter provides accurate Watt, AC/DC Current and Voltage readings regardless of waveforms.

1000A True RMS



DC/AC True Power to 240kW



Features

- True RMS AC Voltage and Current
- DC and AC True Power to 240kW
- 1.2" (30mm) Clamp jaw opening
- Electronic overload protection
- Continuity buzzer & Diode check
- Data Hold function
- DCA Zero function
- Auto Power Off
- Low battery indication
- AC/DC Current

Specifications

Function	Max Range	Max. Resolution	Basic Accuracy
AC Current	1000 A	0.1A	$\pm(2.5\%+5d)$
DC Current	1000 A	0.1A	$\pm(3.0\%+4d)$
AC Voltage	600V	0.1mV	$\pm(0.8\%+2d)$
DC Voltage	600V	0.1mV	$\pm(1.0\%+4d)$
Resistance	40M Ω	0.1 Ω	$\pm(1.0\%+4d)$
Frequency	10MHz	0.01MHz	$\pm(1.2\%+3d)$
AC Power	240kW	10W	$\pm(3.0\%+5d)$
DC Power	240kW	10W	$\pm(2.5\%+5d)$

Size(HxWxD): 229mm x 80mm x 49mm

Weight: 303g

Accessories:

Test leads, gift box with carrying case & 9V battery